

**SUPPORTING MULTIPLE DATA CHANNELS IN A CABLE  
MODEM TERMINATION SYSTEM**

**Technical Field**

5           The present invention relates generally to telecommunications systems, and more specifically to supporting multiple data channels in a cable modem termination system.

**Background**

10           Telecommunications networks provide a mechanism for exchanging data, e.g., voice, video, and other data, between terminal equipment at various locations. One type of telecommunications transmission system is the conventional broadband hybrid fiber/coax (HFC) cable network. Cable networks were originally developed to deliver video and audio content to subscribers over a network of coaxial cables.

15           Over the years, cable networks have evolved. Many cable networks have been updated through the use of fiber optic cable, hence the term hybrid fiber/coax (HFC) networks. In an HFC network, a head end typically is coupled to a plurality of optical distribution nodes through fiber optic cables. The optical distribution nodes are also coupled to coaxial cables that connect terminal equipment with the  
20           network. At the optical distribution node, signals are converted between optical and electrical formats for transmission on the fiber optic cables and the coaxial cables.

            Originally, the HFC networks provided downstream (i.e., from the head end to the terminal equipment) transmission to terminal equipment from audio, video and data sources. Recently, service providers have modified their systems to allow  
25           signals to be transmitted upstream, from the terminal equipment to the head end. This allows services such as telephony, video on demand, pay per view, Internet access and other data services to be provided over the existing coaxial and fiber optic cables, using, for example cable modems, set top boxes and the like.

            One type of cable modem uses a standard referred to as Data Over Cable  
30           Service Interface Specification (DOCSIS). This specification allows equipment developed by different manufacturers to communicate with one another over the

network. The cable modems are connected to the cable network at the subscriber location. The cable modems communicate over the network with a device at the head end referred to as a Cable Modem Termination System (CMTS). A typical CMTS provides a card or chassis with a downstream data port and a number of upstream data ports. Each CMTS allows a service provider to serve a selected number of customers, e.g., one card may be sufficient for 1000 homes on the network.

Demand for data services continues to increase with popularity of the Internet and the like. Thus, service providers continue to increase the capacity of their systems to meet this rising demand. To increase the capacity of their systems, service providers typically install additional CMTS cards and chassis at great expense.

What is needed is a mechanism for increasing the port density of a CMTS within the confines of existing chassis and card sizes.

### Summary

Embodiments of the present invention overcome problems with existing cable modem termination systems (CMTS). Embodiments of a CMTS circuit are provided. Each embodiment provides an increase in the number of subscribers supported by a single CMTS circuit while occupying the same physical space as existing CMTS cards or chassis. For example, the CMTS circuit uses the same physical interface as existing CMTS cards or chassis. In one embodiment, this is accomplished by using a plurality of media access control (MAC) circuits. Each MAC circuit supports a single downstream channel. The downstream channels are combined and upconverted using a single upconverter. Advantageously, the reuse of the upconverter allows sufficient savings in space in the CMTS circuit that multiple downstream channels can be supported in a single CMTS card or chassis.

In one embodiment, a circuit for a cable modem termination system is provided. The circuit includes a backplane interface and a packet processing engine coupled to the backplane interface. The circuit further includes a plurality of media access control (MAC) circuits, each media access control circuit coupled to the

packet processing engine, each MAC circuit supporting one of N contiguous downstream channels with a single upconverter and each MAC circuit also supporting a plurality of upstream channels.

Other embodiments are described and claimed.

5

### **Brief Description of the Drawings**

emb. a17

Figure 1A is a block diagram of one embodiment of a circuit for a cable modem termination system that supports multiple downstream channels according to the teachings of the present invention.

10

Figure 1B is a block diagram of another embodiment of a circuit for a cable modem termination system that supports multiple downstream channels according to the teachings of the present invention.

15

Figure 2 is a graph that illustrates one embodiment a spectrum allocation for downstream data channels for a cable modem termination system according to the teachings of the present invention.

Figure 3 is a graph that illustrates one embodiment of a spectrum allocation for upstream data channels for a cable modem termination system according to the teachings of the present invention.

20

Figure 4 is a block diagram of one embodiment of a system including a cable modem termination system that supports multiple downstream channels according to the teachings of the present invention.

### **Detailed Description**

25

In the following detailed description of the embodiments, reference is made to the accompanying drawings which form a part hereof, and in which is shown by way of illustration specific embodiments in which the invention may be practiced. It is to be understood that other embodiments may be utilized and structural changes may be made without departing from the scope of the present invention.

30

Figure 1A is a block diagram of one embodiment of a circuit, indicated generally at 10, for a cable modem termination system that supports multiple downstream channels according to the teachings of the present invention. Circuit 10 advantageously increases the port density without increasing the size of the card or chassis compared to existing systems by including a plurality of media access control (MAC) circuits 18-1, . . . , 18-N on the same card or chassis. Each of the MAC circuits 18-1, . . . , 18-N supports a separate downstream channel and a separate plurality of upstream channels. In other words, each MAC circuit 18-1, . . . , 18-N supports a separate MAC domain. The added channels allow circuit 10 to provide a higher number of homes passed compared to existing systems. Further, all of MAC circuits 18-1, . . . , 18-N share the same downstream port 24 and the same upstream ports 26-1, . . . , 26-K. Thus, circuit 10 can be used in the same physical space as existing cards or chassis, thereby increasing the port density without requiring a complete modification of the physical structure of existing systems.

Circuit 10 interfaces with a data network. Circuit 10 includes backplane interface 14 which provides a connection through network interface 12 to the data network for circuit 10. Further, circuit 10 includes packet processing engine 16. In one embodiment, packet processing engine 16 is implemented with one or more processors that are programmed to process data packets for the multiple MAC domains of circuit 10.

Circuit 10 also includes MAC circuits 18-1, . . . , 18-N. These MAC circuits 18-1, . . . , 18-N process packets according to the data over cable service interface specification (DOCSIS) standard. Each MAC circuit 18-1, . . . , 18-N operates separately and independently to process packets in a single downstream channel and a plurality of upstream channels. Thus, by increasing the number of MAC circuits, the capacity of the circuit is increased without the need to change the physical interface of cards or chassis incorporating the circuit.

Circuit 10 includes a downstream data or signal path for carrying signals downstream to cable modems over a plurality of downstream data channels. In the downstream direction, MAC circuits 18-1, . . . , 18-N provide data to downstream channels 20. Downstream channels 20 present modulated data at intermediate

frequencies (IF-1, ..., IF-N) that are offset from one another by the channel spacing. The IF signals are provided to upconverter 22. Upconverter 22 provides the upconverted and amplified output to downstream port 24 for transmission.

An example of the output at downstream port 24 is provided in graph 200 of Figure 2. As shown, N contiguous channels in frequency bands 202-1, ..., 202-N of Y MHz bandwidth, respectively, are provided for the N MAC domains. In one embodiment, each channel has a 6 MHz bandwidth. Alternative channel bandwidths are possible. Advantageously, contiguous frequency bands 202-1, ..., 202-N are used such that a single upconverter 22 can be used to prepare the signals of downstream channels 20 for transmission. The use of a single upconverter greatly reduces the expense and space requirements for supporting the multiple MAC domains on circuit 10 by leveraging common circuitry for a number of MAC circuits. Upconverter 22, in one embodiment, is programmable and thus able to produce an output with an appropriate bandwidth to support the number of downstream channels. In one embodiment, upconverter 22 is programmed to place the contiguous downstream channels at any appropriate frequency band within the range of 90 to 870 MHz.

Circuit 10 also receives signals from cable modems in an upstream direction. In the upstream direction, data is received from cable modems at upstream ports 26-1, ..., 26-K. Each of the upstream ports 26-1, ..., 26-K receives data on a plurality of upstream channels. For example, in one embodiment, each port 26-1, ..., 26-K receives N channels of data. Thus, circuit 10 is designed to provide one of the N channels from each port 26-1, ..., 26-K to a corresponding one of MAC circuits 18-1, ..., 18-N. Advantageously, receiving a plurality of channels at each of the upstream ports allows circuit 10 to increase the capacity of a CMTS using a conventional card or chassis size.

Circuit 10 includes upstream channels 28. In one embodiment, upstream channels 28 provides K upstream channels per MAC with each of the upstream channels for a MAC being received at one of upstream ports 26-1, ..., 26-K. Thus, each MAC circuit processes one downstream channel and K upstream channels. Circuit 10 processes N downstream channels and K\*N upstream channels.

In Figure 3, graph 300 illustrates an example of an upstream frequency spectrum for one optical node (see Figure 4) serviced by circuit 10. In this example, upstream channels from a selected optical node are located in the 5-42 MHz frequency range. Each channel for the optical node, e.g., channels 302-1, . . . , 302-K, has a separate and distinct frequency band with one band per port of circuit 10. The frequency allocation for the upstream channels of the other optical nodes serviced by circuit 10 are laid out to allow each node to provide a non-interfering upstream channel to each port of circuit 10. Further, in one embodiment, the frequency bands for the various channels of upstream ports 26-1, . . . , 26-K are not contiguous. Further, it is understood that in other embodiments, the upstream channels are located in other appropriate frequency bands, e.g., 5-65 MHz.

ans. a27 Figure 1B is a block diagram of one embodiment of a circuit, indicated generally at 100, for a cable modem termination system that supports multiple downstream channels according to the teachings of the present invention. Circuit 100 advantageously increases the port density without increasing the size of the card or chassis compared to existing systems by including a plurality of media access control (MAC) circuits 106-1, . . . , 106-N on the same card or chassis. Each of the MAC circuits 106-1, . . . , 106-N supports a separate downstream channel and a separate plurality of upstream channels. In other words, each MAC circuit 106-1, . . . , 106-N supports a separate MAC domain. The added channels allow circuit 100 to provide a higher number of homes passed compared to existing systems. Further, all of MAC circuits 106-1, . . . , 106-N share the same downstream port 114 and the same upstream ports 116-1, . . . , 116-K. Thus, circuit 100 can be used in the same physical space as existing cards or chassis, thereby increasing the port density without requiring a complete modification of the physical structure of existing systems.

Circuit 100 interfaces with a data network. Circuit 100 includes backplane interface 102 which provides a connection through network interface 101 to the data network for circuit 100. Further, circuit 100 includes packet processing engine 104. In one embodiment, packet processing engine 104 is implemented with one or more

processors that are programmed to process data packets for the multiple MAC domains of circuit 100.

Circuit 100 also includes MAC circuits 106-1, . . . , 106-N. These MAC circuits 106-1, . . . , 106-N process packets according to the data over cable service interface specification (DOCSIS) standard. Each MAC circuit 106-1, . . . , 106-N operates separately and independently to process packets in a single downstream channel and a plurality of upstream channels. Thus, by increasing the number of MAC circuits, the capacity of the circuit is increased without the need to change the physical interface of cards or chassis incorporating the circuit.

Circuit 100 includes a downstream data or signal path for carrying signals downstream to cable modems over a plurality of downstream data channels. In the downstream direction, MAC circuits 106-1, . . . , 106-N provide data to downstream modulators 108-1, . . . , 108-N, respectively. Modulators 108-1, . . . , 108-N modulate the data to an intermediate frequency (IF-1, . . . , IF-N) that are offset from one another by the channel spacing. The IF outputs of modulators 108-1, . . . , 108-N are summed in combiner 110 and provided to upconverter 112. Upconverter 112 provides the upconverted and amplified output to downstream port 114 for transmission.

An example of the output at downstream port 114 is provided in graph 200 of Figure 2. As shown, each downstream modulator 108-1, . . . , 108-N is responsible for one of N contiguous channels in frequency bands 202-1, . . . , 202-N of Y MHz bandwidth, respectively. In one embodiment, each modulator 108-1, . . . , 108-N uses a 6 MHz output channel. Alternative channel bandwidths are possible.

Advantageously, contiguous frequency bands 202-1, . . . , 202-N are used such that a single upconverter 112 can be used to prepare the signals from modulators 108-1, . . . , 108-N for transmission. The use of a single upconverter greatly reduces the expense and space requirements for supporting the multiple MAC domains on circuit 100 by leveraging common circuitry for a number of MAC circuits. Upconverter 114, in one embodiment, is programmable and thus able to produce an output with an appropriate bandwidth to support the number of downstream channels. In one

embodiment, upconverter 112 is programmed to place the contiguous downstream channels at any appropriate frequency band within the range of 90 to 870 MHz.

Circuit 100 also receives signals from cable modems in an upstream direction. In the upstream direction, data is received from cable modems at upstream ports 116-1, . . . , 116-K. Each of the upstream ports 116-1, . . . , 116-K receives data on a plurality of upstream channels. For example, in one embodiment, each port 116-1, . . . , 116-K receives N channels of data. Thus, circuit 100 is designed to provide one of the N channels from each port 116-1, . . . , 116-K to a corresponding one of MAC circuits 106-1, . . . , 106-N. Advantageously, receiving a plurality of channels at each of the upstream ports allows circuit 100 to increase the capacity of a CMTS using a conventional card or chassis size.

Splitters 118-1, . . . , 118-K separate out the channels received at their respective ports 116-1, . . . , 116-K. In one embodiment, each splitter 118-1, . . . , 118-K provides N outputs, e.g., 4 outputs or other appropriate number of outputs. Each of the N outputs is coupled through a corresponding receiver/demodulator pair to an input of a corresponding MAC circuit. For example, as shown in Figure 1, splitter 118-1 provides N outputs to receivers 120-1-1, . . . , 120-1-N for downconversion to an intermediate frequency, e.g., a 4 MHz IF signal. In one embodiment, receivers 120-1-1, . . . , 120-1-N are digital receivers that are adapted to receive upstream modulated data signals that have been digitized on the CMTS card from the fiber optic connection from an optical distribution node (See Figure 4). Digital receivers are easily incorporated in circuit 100 and, in one embodiment, all of the digital receivers are incorporated in a single application specific integrated circuit (ASIC). Further, receivers 120-1-1, . . . , 120-1-N are coupled to demodulators 122-1-1, . . . , 122-1-N, respectively. Demodulators 122-1-1, . . . , 122-1-N are coupled to MAC circuits 106-1, . . . , 106-N, respectively. Each of the other receiver/demodulator pairs is connected as shown. In Figure 1, the receivers are designated as 120-X-Y and the demodulators are designated as 122-X-Y. In each case, the X in the reference numeral identifies the associated upstream port for the receiver or demodulator and the Y represents the associated MAC circuit. Thus,



each MAC circuit processes one downstream channel and K upstream channels. Circuit 100 processes N downstream channels and K\*N upstream channels.

In Figure 3, graph 300 illustrates an example of an upstream frequency spectrum for one optical node (see Figure 4) serviced by circuit 100. In this example, upstream channels from a selected optical node are located in the 5-42 MHz frequency range. Each channel for the optical node, e.g., channels 302-1, . . . , 302-K, has a separate and distinct frequency band with one band per port of circuit 100. The frequency allocation for the upstream channels of the other optical nodes serviced by circuit 100 are laid out to allow each node to provide a non-interfering upstream channel to each port of circuit 100. Further, in one embodiment, the frequency bands for the various channels of upstream ports 116-1, . . . , 116-K are not contiguous. Further, it is understood that in other embodiments, the upstream channels are located in other appropriate frequency bands, e.g., 5-65 MHz.

FIG. 4  
FIG. 5  
FIG. 6  
FIG. 7  
FIG. 8  
FIG. 9  
FIG. 10  
FIG. 11  
FIG. 12  
FIG. 13  
FIG. 14  
FIG. 15  
FIG. 16  
FIG. 17  
FIG. 18  
FIG. 19  
FIG. 20  
FIG. 21  
FIG. 22  
FIG. 23  
FIG. 24  
FIG. 25  
FIG. 26  
FIG. 27  
FIG. 28  
FIG. 29  
FIG. 30  
FIG. 31  
FIG. 32  
FIG. 33  
FIG. 34  
FIG. 35  
FIG. 36  
FIG. 37  
FIG. 38  
FIG. 39  
FIG. 40  
FIG. 41  
FIG. 42  
FIG. 43  
FIG. 44  
FIG. 45  
FIG. 46  
FIG. 47  
FIG. 48  
FIG. 49  
FIG. 50  
FIG. 51  
FIG. 52  
FIG. 53  
FIG. 54  
FIG. 55  
FIG. 56  
FIG. 57  
FIG. 58  
FIG. 59  
FIG. 60  
FIG. 61  
FIG. 62  
FIG. 63  
FIG. 64  
FIG. 65  
FIG. 66  
FIG. 67  
FIG. 68  
FIG. 69  
FIG. 70  
FIG. 71  
FIG. 72  
FIG. 73  
FIG. 74  
FIG. 75  
FIG. 76  
FIG. 77  
FIG. 78  
FIG. 79  
FIG. 80  
FIG. 81  
FIG. 82  
FIG. 83  
FIG. 84  
FIG. 85  
FIG. 86  
FIG. 87  
FIG. 88  
FIG. 89  
FIG. 90  
FIG. 91  
FIG. 92  
FIG. 93  
FIG. 94  
FIG. 95  
FIG. 96  
FIG. 97  
FIG. 98  
FIG. 99  
FIG. 100  
FIG. 101  
FIG. 102  
FIG. 103  
FIG. 104  
FIG. 105  
FIG. 106  
FIG. 107  
FIG. 108  
FIG. 109  
FIG. 110  
FIG. 111  
FIG. 112  
FIG. 113  
FIG. 114  
FIG. 115  
FIG. 116  
FIG. 117  
FIG. 118  
FIG. 119  
FIG. 120  
FIG. 121  
FIG. 122  
FIG. 123  
FIG. 124  
FIG. 125  
FIG. 126  
FIG. 127  
FIG. 128  
FIG. 129  
FIG. 130  
FIG. 131  
FIG. 132  
FIG. 133  
FIG. 134  
FIG. 135  
FIG. 136  
FIG. 137  
FIG. 138  
FIG. 139  
FIG. 140  
FIG. 141  
FIG. 142  
FIG. 143  
FIG. 144  
FIG. 145  
FIG. 146  
FIG. 147  
FIG. 148  
FIG. 149  
FIG. 150  
FIG. 151  
FIG. 152  
FIG. 153  
FIG. 154  
FIG. 155  
FIG. 156  
FIG. 157  
FIG. 158  
FIG. 159  
FIG. 160  
FIG. 161  
FIG. 162  
FIG. 163  
FIG. 164  
FIG. 165  
FIG. 166  
FIG. 167  
FIG. 168  
FIG. 169  
FIG. 170  
FIG. 171  
FIG. 172  
FIG. 173  
FIG. 174  
FIG. 175  
FIG. 176  
FIG. 177  
FIG. 178  
FIG. 179  
FIG. 180  
FIG. 181  
FIG. 182  
FIG. 183  
FIG. 184  
FIG. 185  
FIG. 186  
FIG. 187  
FIG. 188  
FIG. 189  
FIG. 190  
FIG. 191  
FIG. 192  
FIG. 193  
FIG. 194  
FIG. 195  
FIG. 196  
FIG. 197  
FIG. 198  
FIG. 199  
FIG. 200  
FIG. 201  
FIG. 202  
FIG. 203  
FIG. 204  
FIG. 205  
FIG. 206  
FIG. 207  
FIG. 208  
FIG. 209  
FIG. 210  
FIG. 211  
FIG. 212  
FIG. 213  
FIG. 214  
FIG. 215  
FIG. 216  
FIG. 217  
FIG. 218  
FIG. 219  
FIG. 220  
FIG. 221  
FIG. 222  
FIG. 223  
FIG. 224  
FIG. 225  
FIG. 226  
FIG. 227  
FIG. 228  
FIG. 229  
FIG. 230  
FIG. 231  
FIG. 232  
FIG. 233  
FIG. 234  
FIG. 235  
FIG. 236  
FIG. 237  
FIG. 238  
FIG. 239  
FIG. 240  
FIG. 241  
FIG. 242  
FIG. 243  
FIG. 244  
FIG. 245  
FIG. 246  
FIG. 247  
FIG. 248  
FIG. 249  
FIG. 250  
FIG. 251  
FIG. 252  
FIG. 253  
FIG. 254  
FIG. 255  
FIG. 256  
FIG. 257  
FIG. 258  
FIG. 259  
FIG. 260  
FIG. 261  
FIG. 262  
FIG. 263  
FIG. 264  
FIG. 265  
FIG. 266  
FIG. 267  
FIG. 268  
FIG. 269  
FIG. 270  
FIG. 271  
FIG. 272  
FIG. 273  
FIG. 274  
FIG. 275  
FIG. 276  
FIG. 277  
FIG. 278  
FIG. 279  
FIG. 280  
FIG. 281  
FIG. 282  
FIG. 283  
FIG. 284  
FIG. 285  
FIG. 286  
FIG. 287  
FIG. 288  
FIG. 289  
FIG. 290  
FIG. 291  
FIG. 292  
FIG. 293  
FIG. 294  
FIG. 295  
FIG. 296  
FIG. 297  
FIG. 298  
FIG. 299  
FIG. 300  
FIG. 301  
FIG. 302  
FIG. 303  
FIG. 304  
FIG. 305  
FIG. 306  
FIG. 307  
FIG. 308  
FIG. 309  
FIG. 310  
FIG. 311  
FIG. 312  
FIG. 313  
FIG. 314  
FIG. 315  
FIG. 316  
FIG. 317  
FIG. 318  
FIG. 319  
FIG. 320  
FIG. 321  
FIG. 322  
FIG. 323  
FIG. 324  
FIG. 325  
FIG. 326  
FIG. 327  
FIG. 328  
FIG. 329  
FIG. 330  
FIG. 331  
FIG. 332  
FIG. 333  
FIG. 334  
FIG. 335  
FIG. 336  
FIG. 337  
FIG. 338  
FIG. 339  
FIG. 340  
FIG. 341  
FIG. 342  
FIG. 343  
FIG. 344  
FIG. 345  
FIG. 346  
FIG. 347  
FIG. 348  
FIG. 349  
FIG. 350  
FIG. 351  
FIG. 352  
FIG. 353  
FIG. 354  
FIG. 355  
FIG. 356  
FIG. 357  
FIG. 358  
FIG. 359  
FIG. 360  
FIG. 361  
FIG. 362  
FIG. 363  
FIG. 364  
FIG. 365  
FIG. 366  
FIG. 367  
FIG. 368  
FIG. 369  
FIG. 370  
FIG. 371  
FIG. 372  
FIG. 373  
FIG. 374  
FIG. 375  
FIG. 376  
FIG. 377  
FIG. 378  
FIG. 379  
FIG. 380  
FIG. 381  
FIG. 382  
FIG. 383  
FIG. 384  
FIG. 385  
FIG. 386  
FIG. 387  
FIG. 388  
FIG. 389  
FIG. 390  
FIG. 391  
FIG. 392  
FIG. 393  
FIG. 394  
FIG. 395  
FIG. 396  
FIG. 397  
FIG. 398  
FIG. 399  
FIG. 400  
FIG. 401  
FIG. 402  
FIG. 403  
FIG. 404  
FIG. 405  
FIG. 406  
FIG. 407  
FIG. 408  
FIG. 409  
FIG. 410  
FIG. 411  
FIG. 412  
FIG. 413  
FIG. 414  
FIG. 415  
FIG. 416  
FIG. 417  
FIG. 418  
FIG. 419  
FIG. 420  
FIG. 421  
FIG. 422  
FIG. 423  
FIG. 424  
FIG. 425  
FIG. 426  
FIG. 427  
FIG. 428  
FIG. 429  
FIG. 430  
FIG. 431  
FIG. 432  
FIG. 433  
FIG. 434  
FIG. 435  
FIG. 436  
FIG. 437  
FIG. 438  
FIG. 439  
FIG. 440  
FIG. 441  
FIG. 442  
FIG. 443  
FIG. 444  
FIG. 445  
FIG. 446  
FIG. 447  
FIG. 448  
FIG. 449  
FIG. 450  
FIG. 451  
FIG. 452  
FIG. 453  
FIG. 454  
FIG. 455  
FIG. 456  
FIG. 457  
FIG. 458  
FIG. 459  
FIG. 460  
FIG. 461  
FIG. 462  
FIG. 463  
FIG. 464  
FIG. 465  
FIG. 466  
FIG. 467  
FIG. 468  
FIG. 469  
FIG. 470  
FIG. 471  
FIG. 472  
FIG. 473  
FIG. 474  
FIG. 475  
FIG. 476  
FIG. 477  
FIG. 478  
FIG. 479  
FIG. 480  
FIG. 481  
FIG. 482  
FIG. 483  
FIG. 484  
FIG. 485  
FIG. 486  
FIG. 487  
FIG. 488  
FIG. 489  
FIG. 490  
FIG. 491  
FIG. 492  
FIG. 493  
FIG. 494  
FIG. 495  
FIG. 496  
FIG. 497  
FIG. 498  
FIG. 499  
FIG. 500  
FIG. 501  
FIG. 502  
FIG. 503  
FIG. 504  
FIG. 505  
FIG. 506  
FIG. 507  
FIG. 508  
FIG. 509  
FIG. 510  
FIG. 511  
FIG. 512  
FIG. 513  
FIG. 514  
FIG. 515  
FIG. 516  
FIG. 517  
FIG. 518  
FIG. 519  
FIG. 520  
FIG. 521  
FIG. 522  
FIG. 523  
FIG. 524  
FIG. 525  
FIG. 526  
FIG. 527  
FIG. 528  
FIG. 529  
FIG. 530  
FIG. 531  
FIG. 532  
FIG. 533  
FIG. 534  
FIG. 535  
FIG. 536  
FIG. 537  
FIG. 538  
FIG. 539  
FIG. 540  
FIG. 541  
FIG. 542  
FIG. 543  
FIG. 544  
FIG. 545  
FIG. 546  
FIG. 547  
FIG. 548  
FIG. 549  
FIG. 550  
FIG. 551  
FIG. 552  
FIG. 553  
FIG. 554  
FIG. 555  
FIG. 556  
FIG. 557  
FIG. 558  
FIG. 559  
FIG. 560  
FIG. 561  
FIG. 562  
FIG. 563  
FIG. 564  
FIG. 565  
FIG. 566  
FIG. 567  
FIG. 568  
FIG. 569  
FIG. 570  
FIG. 571  
FIG. 572  
FIG. 573  
FIG. 574  
FIG. 575  
FIG. 576  
FIG. 577  
FIG. 578  
FIG. 579  
FIG. 580  
FIG. 581  
FIG. 582  
FIG. 583  
FIG. 584  
FIG. 585  
FIG. 586  
FIG. 587  
FIG. 588  
FIG. 589  
FIG. 590  
FIG. 591  
FIG. 592  
FIG. 593  
FIG. 594  
FIG. 595  
FIG. 596  
FIG. 597  
FIG. 598  
FIG. 599  
FIG. 600  
FIG. 601  
FIG. 602  
FIG. 603  
FIG. 604  
FIG. 605  
FIG. 606  
FIG. 607  
FIG. 608  
FIG. 609  
FIG. 610  
FIG. 611  
FIG. 612  
FIG. 613  
FIG. 614  
FIG. 615  
FIG. 616  
FIG. 617  
FIG. 618  
FIG. 619  
FIG. 620  
FIG. 621  
FIG. 622  
FIG. 623  
FIG. 624  
FIG. 625  
FIG. 626  
FIG. 627  
FIG. 628  
FIG. 629  
FIG. 630  
FIG. 631  
FIG. 632  
FIG. 633  
FIG. 634  
FIG. 635  
FIG. 636  
FIG. 637  
FIG. 638  
FIG. 639  
FIG. 640  
FIG. 641  
FIG. 642  
FIG. 643  
FIG. 644  
FIG. 645  
FIG. 646  
FIG. 647  
FIG. 648  
FIG. 649  
FIG. 650  
FIG. 651  
FIG. 652  
FIG. 653  
FIG. 654  
FIG. 655  
FIG. 656  
FIG. 657  
FIG. 658  
FIG. 659  
FIG. 660  
FIG. 661  
FIG. 662  
FIG. 663  
FIG. 664  
FIG. 665  
FIG. 666  
FIG. 667  
FIG. 668  
FIG. 669  
FIG. 670  
FIG. 671  
FIG. 672  
FIG. 673  
FIG. 674  
FIG. 675  
FIG. 676  
FIG. 677  
FIG. 678  
FIG. 679  
FIG. 680  
FIG. 681  
FIG. 682  
FIG. 683  
FIG. 684  
FIG. 685  
FIG. 686  
FIG. 687  
FIG. 688  
FIG. 689  
FIG. 690  
FIG. 691  
FIG. 692  
FIG. 693  
FIG. 694  
FIG. 695  
FIG. 696  
FIG. 697  
FIG. 698  
FIG. 699  
FIG. 700  
FIG. 701  
FIG. 702  
FIG. 703  
FIG. 704  
FIG. 705  
FIG. 706  
FIG. 707  
FIG. 708  
FIG. 709  
FIG. 710  
FIG. 711  
FIG. 712  
FIG. 713  
FIG. 714  
FIG. 715  
FIG. 716  
FIG. 717  
FIG. 718  
FIG. 719  
FIG. 720  
FIG. 721  
FIG. 722  
FIG. 723  
FIG. 724  
FIG. 725  
FIG. 726  
FIG. 727  
FIG. 728  
FIG. 729  
FIG. 730  
FIG. 731  
FIG. 732  
FIG. 733  
FIG. 734  
FIG. 735  
FIG. 736  
FIG. 737  
FIG. 738  
FIG. 739  
FIG. 740  
FIG. 741  
FIG. 742  
FIG. 743  
FIG. 744  
FIG. 745  
FIG. 746  
FIG. 747  
FIG. 748  
FIG. 749  
FIG. 750  
FIG. 751  
FIG. 752  
FIG. 753  
FIG. 754  
FIG. 755  
FIG. 756  
FIG. 757  
FIG. 758  
FIG. 759  
FIG. 760  
FIG. 761  
FIG. 762  
FIG. 763  
FIG. 764  
FIG. 765  
FIG. 766  
FIG. 767  
FIG. 768  
FIG. 769  
FIG. 770  
FIG. 771  
FIG. 772  
FIG. 773  
FIG. 774  
FIG. 775  
FIG. 776  
FIG. 777  
FIG. 778  
FIG. 779  
FIG. 780  
FIG. 781  
FIG. 782  
FIG. 783  
FIG. 784  
FIG. 785  
FIG. 786  
FIG. 787  
FIG. 788  
FIG. 789  
FIG. 790  
FIG. 791  
FIG. 792  
FIG. 793  
FIG. 794  
FIG. 795  
FIG. 796  
FIG. 797  
FIG. 798  
FIG. 799  
FIG. 800  
FIG. 801  
FIG. 802  
FIG. 803  
FIG. 804  
FIG. 805  
FIG. 806  
FIG. 807  
FIG. 808  
FIG. 809  
FIG. 810  
FIG. 811  
FIG. 812  
FIG. 813  
FIG. 814  
FIG. 815  
FIG. 816  
FIG. 817  
FIG. 818  
FIG. 819  
FIG. 820  
FIG. 821  
FIG. 822  
FIG. 823  
FIG. 824  
FIG. 825  
FIG. 826  
FIG. 827  
FIG. 828  
FIG. 829  
FIG. 830  
FIG. 831  
FIG. 832  
FIG. 833  
FIG. 834  
FIG. 835  
FIG. 836  
FIG. 837  
FIG. 838  
FIG. 839  
FIG. 840  
FIG. 841  
FIG. 842  
FIG. 843  
FIG. 844  
FIG. 845  
FIG. 846  
FIG. 847  
FIG. 848  
FIG. 849  
FIG. 850  
FIG. 851  
FIG. 852  
FIG. 853  
FIG. 854  
FIG. 855  
FIG. 856  
FIG. 857  
FIG. 858  
FIG. 859  
FIG. 860  
FIG. 861  
FIG. 862  
FIG. 863  
FIG. 864  
FIG. 865  
FIG. 866  
FIG. 867  
FIG. 868  
FIG. 869  
FIG. 870  
FIG. 871  
FIG. 872  
FIG. 873  
FIG. 874  
FIG. 875  
FIG. 876  
FIG. 877  
FIG. 878  
FIG. 879  
FIG. 880  
FIG. 881  
FIG. 882  
FIG. 883  
FIG. 884  
FIG. 885  
FIG. 886  
FIG. 887  
FIG. 888  
FIG. 889  
FIG. 890  
FIG. 891  
FIG. 892  
FIG. 893  
FIG. 894  
FIG. 895  
FIG. 896  
FIG. 897  
FIG. 898  
FIG. 899  
FIG. 900  
FIG. 901  
FIG. 902  
FIG. 903  
FIG. 904  
FIG. 905  
FIG. 906  
FIG. 907  
FIG. 908  
FIG. 909  
FIG. 910  
FIG. 911  
FIG. 912  
FIG. 913  
FIG. 914  
FIG. 915  
FIG. 916  
FIG. 917  
FIG. 918  
FIG. 919  
FIG. 920  
FIG. 921  
FIG. 922  
FIG. 923  
FIG. 924  
FIG. 925  
FIG. 926  
FIG. 927  
FIG. 928  
FIG. 929  
FIG. 930  
FIG. 931  
FIG. 932  
FIG. 933  
FIG. 934  
FIG. 935  
FIG. 936  
FIG. 937  
FIG. 938  
FIG. 939  
FIG. 940  
FIG. 941  
FIG. 942  
FIG. 943  
FIG. 944  
FIG. 945  
FIG. 946  
FIG. 947  
FIG. 948  
FIG. 949  
FIG. 950  
FIG. 951  
FIG. 952  
FIG. 953  
FIG. 954  
FIG. 955  
FIG. 956  
FIG. 957  
FIG. 958  
FIG. 959  
FIG. 960  
FIG. 961  
FIG. 962  
FIG. 963  
FIG. 964  
FIG. 965  
FIG. 966  
FIG. 967  
FIG. 968  
FIG. 969  
FIG. 970  
FIG. 971  
FIG. 972  
FIG. 973  
FIG. 974  
FIG. 975  
FIG. 976  
FIG. 977  
FIG. 978  
FIG. 979  
FIG. 980  
FIG. 981  
FIG. 982  
FIG. 983  
FIG. 984  
FIG. 985  
FIG. 986  
FIG. 987  
FIG. 988  
FIG. 989  
FIG. 990  
FIG. 991  
FIG. 992  
FIG. 993  
FIG. 994  
FIG. 995  
FIG. 996  
FIG. 997  
FIG. 998  
FIG. 999  
FIG. 1000

FIG. 4 is a block diagram of one embodiment of a system, indicated generally at 400, including a multi-channel cable modem termination system 404 that supports multiple downstream channels according to the teachings of the present invention. System 400 includes head end 402. Among other components, head end 402 includes a multi-channel CMTS 404 that supports multiple downstream channels and multiple upstream channels on a single card or chassis. Advantageously, CMTS 404 has a physical configuration that uses the same number of upstream and downstream ports as in existing cards and chassis, but provides more downstream and upstream channels than existing cards and chassis. Thus, CMTS 404 allows a larger number of subscribers to be supported than existing CMTS cards and chassis. In one embodiment, CMTS 404 is constructed as described above with respect to Figures 1A, 1B, 2, and/or 3.

Head end 402 is coupled to a plurality of optical distribution nodes 406-1, . . . , 406-N. Each optical distribution node represents a separate MAC domain for CMTS 404. Head end 402 is coupled to optical distribution nodes 406-1, . . . , 406-N over downstream optical fibers 414. Each of optical distribution nodes 406-1, . . . , 406-N is further coupled to a distribution network of coaxial cables represented by coaxial cable 416. Each of optical distribution nodes 406-1, . . . , 406-N includes

circuitry that is adapted to convert optical signals from head end 402 into electrical signals for transmission over coaxial cable. Further, optical distribution nodes 406-1, . . . , 406-N each include circuitry that is further adapted to convert electrical signals from coaxial cables to optical signals for transmission to head end 402.

5           Coaxial cable 416 provides connection for terminal equipment to network 400. For example, taps, represented by tap 418, provide a connection mechanism for terminal equipment, such as cable modem 408. In one embodiment, cable modem 408 comprises a cable modem according to the data over cable service interface specification (DOCSIS) standard

10           Head end 402 provides a downstream path for data from CMTS 404. The downstream data path includes electrical to optical converter (E/O) 410 coupled in series with splitter 412 between the downstream port (DS) of CMTS 404 and optical fibers 414. In this manner, the downstream data signals from CMTS 404 are provided over optical fibers 414 to optical distribution nodes 406-1, . . . , 406-N for  
15           distribution to selected terminal equipment.

            Head end 402 also includes an upstream path for data from terminal equipment. In the upstream, optical distribution nodes 406-1, . . . , 406-N are coupled to optical to electrical converters (O/E) 422-1, . . . , 422-N, respectively, over upstream optical fibers 420. Each of the upstream optical fibers 420 carries a  
20           plurality of upstream channels and is coupled to one of upstream ports, US1, . . . , USK, of CMTS 404.

### **Conclusion**

            Embodiments of the present invention have been described. In these embodiments, a cable modem termination system (CMTS) is provided that provides  
25           an increase in the number of subscribers supported by a single CMTS card or chassis while using the same physical interface to the system. In one embodiment, this is accomplished by using a plurality of media access control (MAC) circuits. Each MAC circuit supports a single downstream channel. The downstream channels are combined and upconverted using a single upconverter. Advantageously, the reuse of  
30           the upconverter allows sufficient savings in space on the CMTS card or chassis that multiple downstream channels can be supported.

